















The popular Saturn product is now available in LED using industry leading Tridonic control gear offering a five year warranty.

Integral 3 hour maintained emergency versions along with microwave presence detection and dimming control provide a complete solution for stairwells and corridors.

Manufactured in the UK with Tridonic Generation 4 LED Boards and Drivers

Features:

- LED bulkhead with 5 year warranty
- UK designed and developed
- Emergency and Self Test options
- DALI,1-10V, Phase Dim & other dimming options available
- High output diffuser
- Approved to BS EN60598-2-22
- Various sizes and finishes
- IP20
- Featuring new Generation 4 Tridonic LED Board and Driver

Dimensions:

| SAT3G4 | 325mm x 95mm |
|--------|---------------|
| SAT4G4 | 425mm x 95mm |
| SAT5G4 | 525mm x 105mm |















| Option 1 | |
|---------------------------------------|--|
| SAT3G4 | 325mm x 95mm |
| SAT4G4 | 425mm x 95mm |
| SAT5G4 | 525mm x 105mm |
| Option 2 | |
| 12W30 | 12W LED 3000K 1305lm |
| 12W40 | 12W LED 4000K 1365lm |
| 18W30 | 18W LED 3000K 1700lm |
| 18W40 | 18W LED 4000K 1782lm |
| 22W30 | 22W LED 3000K 2490lm (not available in SAT3 size) |
| 22W40 | 22W LED 4000K 2605lm (not available in SAT3 size) |
| 31W30 | 31W LED 3000K 3643Im (not available in SAT3 size) |
| 31W40 | 31W LED 4000K 3811Im (not available in SAT3 size) |
| Option 3 | |
| | |
| WH | White Base - Opal LED Diffuser |
| | White Base - Opal LED Diffuser Chrome Base - Opal LED Diffuser |
| WH | |
| WH CH | Chrome Base - Opal LED Diffuser |
| WH CH BR | Chrome Base - Opal LED Diffuser |
| WH CH BR Option 4 | Chrome Base - Opal LED Diffuser Brass Base - Opal LED Diffuser |
| WH CH BR Option 4 -01 | Chrome Base - Opal LED Diffuser Brass Base - Opal LED Diffuser LED Standard |
| WH CH BR Option 4 -01 -02 | Chrome Base - Opal LED Diffuser Brass Base - Opal LED Diffuser LED Standard c/w Microwave |
| WH CH BR Option 4 -01 -02 -03 | Chrome Base - Opal LED Diffuser Brass Base - Opal LED Diffuser LED Standard c/w Microwave c/w Corridor Function |
| WH CH BR Option 4 -01 -02 -03 -04 | Chrome Base - Opal LED Diffuser Brass Base - Opal LED Diffuser LED Standard c/w Microwave c/w Corridor Function c/w Microwave & Corridor Function |
| WH CH BR Option 4 -01 -02 -03 -04 -05 | Chrome Base - Opal LED Diffuser Brass Base - Opal LED Diffuser LED Standard c/w Microwave c/w Corridor Function c/w Microwave & Corridor Function c/w Emergency M3 |

Ordering Part no. Format: Option1Option2Option3Option4

Example: SAT4G418W40WH-02 Saturn 425mm Generation4 18w 4000k white c/w microwave

^{*} Please contact our sales office for Dimming & other options